




Convergence Board + G2 Adjusting / Switching (761289)


7612166





46





IC5 TL084

1 0V	8 0V
2 0V	9 0V
3 0V	10 0V
4 12.2V	11 -12V
5 0V	12 0V
6 0V	13 0V
7 0V	14 0V

IC6 & IC7 TL084

1 -0.9V	8 1.2V
2 0V	9 1.2V
3 0V	10 1.2V
4 12.2V	11 -12V
5 0V	12 0V
6 0V	13 0V
7 0.9V	14 -1.2V

IC8 TL084

1 1.3V	8 4.2V
2 1.3V	9 0V
3 1.3V	10 0V
4 12.2V	11 -12V
5 1.3V	12 0V
6 1.3V	13 0V
7 1.3V	14 0V

IC9 TL084

1 -1.3V	8 -10.1V
2 0V	9 0V
3 0V	10 0V
4 12.2V	11 -11.4V
5 0V	12 0V
6 0V	13 0V
7 -1.3V	14 0V

IC11 TL084


1 0.5V	8 0V
2 0V	9 0V
3 0V	10 0V
4 12.2V	11 -12V
5 0V	12 0V
6 0V	13 0V
7 -0.2V	14 0.1V

IC1 TL084

1 -0.9V	8 -0.9V
2 -0.9V	9 0V
3 -0.9V	10 0V
4 12.2V	11 -12V
5 0V	12 0.9V
6 0V	13 0.9V
7 0.9V	14 0.9V

IC10 TL084

1 1.2V	8 1.2V
2 1.2V	9 0V
3 1.2V	10 0V
4 12.2V	11 -12V
5 0V	12 -12V
6 0V	13 -12V
7 -1.2V	14 -1.2V



IC1 TL084
1 0.0V 8 -0.9V
2 0.0V 9 0V
3 0.0V 10 0V
4 1.2V 11 -1.2V
5 0.0V 12 -1.2V
6 0.0V 13 -1.2V
7 0.0V 14 -1.2V

IC10 TL084
1 1.2V 8 1.2V
2 1.2V 9 0V
3 1.2V 10 0V
4 1.2V 11 -1.2V
5 0.0V 12 -1.2V
6 0.0V 13 -1.2V
7 -1.2V 14 -1.2V

IC12 TL084
1 0.4V 8 -0.4V
2 0.4V 9 0V
3 0.4V 10 0V
4 1.2V 11 -1.2V
5 -0.4V 12 0V
6 -0.4V 13 0V
7 -0.4V 14 -0.4V

IC14,15,16,17 1496
1 0V 8 5.3V
2 -0.7V 9 0V
3 -0.7V 10 5.3V
4 0V 11 0V
5 -10.3V 12 11V
6 8.2V 13 0V
7 0V 14 -11.4V

IC20 TL084
1 0.2V 8 -0.8V
2 0.2V 9 0V
3 0.2V 10 0V
4 1.1V 11 -1.1V
5 0.2V 12 0V
6 0.2V 13 0V
7 0.1V 14 -0.4V

MODIFICATIONS RESERVED

R	Name	CONVERGENCE	Article no.	76 12165
C	Date	25/06/85	Drawn	CD
Q	BARCO Electronic		Checked	

76 12165

ITEM NO.	SIT.	DESCRIPTION	ITEM NO.	SIT.	DESCRIPTION
-----	----	-----	-----	----	-----
11 1494	C..1	CAPACITOR ELPR 10M Z5 63			
11 2683	C..2	CAPACITOR N750MI 22P G5 500			
11 5932	C..3	CAPACITOR PP RA 4K7 J5 63	11 37121	C.97	CAPACITOR POME 10K K5 100
11 3724	C..4	CAPACITOR POME 100K K5 63	13 1910	D..1	DIODE BY207 RECTIFIER
11 3724	C..5	CAPACITOR POME 100K K5 63	13 1636	D..2	DIODE BAT43 SD101 SCHOTTKY
11 59061	C..6	CAPACITOR PP RA 390P J5 100	13 1636	D..3	DIODE BAT43 SD101 SCHOTTKY
11 3724	C..7	CAPACITOR POME 100K K5 63	13 1636	D..4	DIODE BAT43 SD101 SCHOTTKY
11 3724	C..8	CAPACITOR POME 100K K5 63	13 1636	D..5	DIODE BAT43 SD101 SCHOTTKY
11 3724	C..9	CAPACITOR POME 100K K5 63	13 1636	D..6	DIODE BAT43 SD101 SCHOTTKY
11 2774	C.10	CAPACITOR CE MI 100K U5 63	13 1636	D..7	DIODE BAT43 SD101 SCHOTTKY
11 2774	C.11	CAPACITOR CE MI 100K U5 63	13 1636	D..8	DIODE BAT43 SD101 SCHOTTKY
11 1531	C.12	CAPACITOR ELPRMI 10M M5 35	13 1636	D..9	DIODE BAT43 SD101 SCHOTTKY
11 1531	C.13	CAPACITOR ELPRMI 10M M5 35	13 1636	D.10	DIODE BAT43 SD101 SCHOTTKY
11 1531	C.14	CAPACITOR ELPRMI 10M M5 35	13 1628	D.11	DIODE BAW62 SWITCH
11 1531	C.15	CAPACITOR ELPRMI 10M M5 35	13 1628	D.12	DIODE BAW62 SWITCH
11 3724	C.16	CAPACITOR POME 100K K5 63			
11 3724	C.17	CAPACITOR POME 100K K5 63	13 4113	I..1	INTEGRATED CIRCUIT TL084
11 3724	C.18	CAPACITOR POME 100K K5 63	13 4113	I..2	INTEGRATED CIRCUIT TL084
11 3724	C.19	CAPACITOR POME 100K K5 63	13 7297	I..3	INTEGRATED CIRCUIT 3054
11 3720	C.25	CAPACITOR POME 47K K5 63	13 7297	I..4	INTEGRATED CIRCUIT 3054
11 1477	C.26	CAPACITOR ELPR 100M Z5 25	13 4113	I..5	INTEGRATED CIRCUIT TL084
11 1550	C.27	CAPACITOR ELPRMI 4M7 M5 50	13 4113	I..6	INTEGRATED CIRCUIT TL084
11 1550	C.28	CAPACITOR ELPRMI 4M7 M5 50	13 4113	I..7	INTEGRATED CIRCUIT TL084
11 1550	C.29	CAPACITOR ELPRMI 4M7 M5 50	13 4113	I..8	INTEGRATED CIRCUIT TL084
11 1550	C.30	CAPACITOR ELPRMI 4M7 M5 50	13 4113	I..9	INTEGRATED CIRCUIT TL084
11 1680	C.31	CAPACITOR ELRABI 10M V 40	13 4113	I.10	INTEGRATED CIRCUIT TL084
11 1680	C.32	CAPACITOR ELRABI 10M V 40	13 4113	I.11	INTEGRATED CIRCUIT TL084
11 2683	C.34	CAPACITOR N750MI 22P G5 500	13 4113	I.12	INTEGRATED CIRCUIT TL084
11 5932	C.35	CAPACITOR PP RA 4K7 J5 63	13 4113	I.13	INTEGRATED CIRCUIT TL084
11 22415	C.36	CAPACITOR NPO MI 82P J5 63	13 27655	I.14	INTEGRATED CIRCUIT MC1496
11 11565	C.37	CAPACITOR ELAX 10M Z 25	13 27655	I.15	INTEGRATED CIRCUIT MC1496
11 11565	C.38	CAPACITOR ELAX 10M Z 25	13 27655	I.16	INTEGRATED CIRCUIT MC1496
11 3730	C.39	CAPACITOR POME 330K K5 63	13 27655	I.17	INTEGRATED CIRCUIT MC1496
11 2774	C.40	CAPACITOR CE MI 100K U5 63	13 4113	I.20	INTEGRATED CIRCUIT TL084
11 1546	C.41	CAPACITOR ELPRMI 1M M5 50	13 2751	I.21	INTEGRATED CIRCUIT TDA2030V
11 1548	C.42	CAPACITOR ELPRMI 2M2 M5 50	13 2751	I.22	INTEGRATED CIRCUIT TDA2030V
11 11565	C.43	CAPACITOR ELAX 10M Z 25	13 2751	I.23	INTEGRATED CIRCUIT TDA2030V
11 3728	C.44	CAPACITOR POME 220K K5 63	13 2751	I.24	INTEGRATED CIRCUIT TDA2030V
11 11565	C.50	CAPACITOR ELAX 10M Z 25	13 2751	I.25	INTEGRATED CIRCUIT TDA2030V
11 2747	C.51	CAPACITOR CE MI 4K7 K5 63	13 4002	I.27	INTEGRATED CIRCUIT 7812
11 2774	C.52	CAPACITOR CE MI 100K U5 63	13 4016	I.28	INTEGRATED CIRCUIT 7912
11 3724	C.53	CAPACITOR POME 100K K5 63			
11 2366	C.54	CAPACITOR N750MI 220P J5 63	10 67291	P..1	TRIMPOT CEMH 10K K OW50
11 2774	C.55	CAPACITOR CE MI 100K U5 63	10 67291	P..2	TRIMPOT CEMH 10K K OW50
11 2774	C.56	CAPACITOR CE MI 100K U5 63	10 67291	P..3	TRIMPOT CEMH 10K K OW50
11 37121	C.57	CAPACITOR POME 10K K5 100	10 67291	P..4	TRIMPOT CEMH 10K K OW50
11 11565	C.60	CAPACITOR ELAX 10M Z 25	10 67291	P..5	TRIMPOT CEMH 10K K OW50
11 2747	C.61	CAPACITOR CE MI 4K7 K5 63	10 67291	P..6	TRIMPOT CEMH 10K K OW50
11 2774	C.62	CAPACITOR CE MI 100K U5 63	10 67291	P..7	TRIMPOT CEMH 10K K OW50
11 3724	C.63	CAPACITOR POME 100K K5 63	10 67291	P..8	TRIMPOT CEMH 10K K OW50
11 2366	C.64	CAPACITOR N750MI 220P J5 63	10 67291	P..9	TRIMPOT CEMH 10K K OW50
11 2774	C.65	CAPACITOR CE MI 100K U5 63	10 67291	P.10	TRIMPOT CEMH 10K K OW50
11 2774	C.66	CAPACITOR CE MI 100K U5 63	10 67291	P.11	TRIMPOT CEMH 10K K OW50
11 37121	C.67	CAPACITOR POME 10K K5 100	10 67291	P.14	TRIMPOT CEMH 10K K OW50
11 11565	C.70	CAPACITOR ELAX 10M Z 25	10 67291	P.15	TRIMPOT CEMH 10K K OW50
11 2747	C.71	CAPACITOR CE MI 4K7 K5 63	10 67291	P.16	TRIMPOT CEMH 10K K OW50
11 2774	C.72	CAPACITOR CE MI 100K U5 63	10 67291	P.17	TRIMPOT CEMH 10K K OW50
11 3724	C.73	CAPACITOR POME 100K K5 63	10 67291	P.18	TRIMPOT CEMH 10K K OW50
11 2366	C.74	CAPACITOR N750MI 220P J5 63	10 67291	P.19	TRIMPOT CEMH 10K K OW50
11 2774	C.75	CAPACITOR CE MI 100K U5 63	10 67291	P.21	TRIMPOT CEMH 10K K OW50
11 2774	C.76	CAPACITOR CE MI 100K U5 63	10 67291	P.22	TRIMPOT CEMH 10K K OW50
11 37121	C.77	CAPACITOR POME 10K K5 100	10 67291	P.25	TRIMPOT CEMH 10K K OW50
11 11565	C.80	CAPACITOR ELAX 10M Z 25	10 67291	P.27	TRIMPOT CEMH 10K K OW50
11 2747	C.81	CAPACITOR CE MI 4K7 K5 63	10 67291	P.28	TRIMPOT CEMH 10K K OW50
11 2774	C.82	CAPACITOR CE MI 100K U5 63	10 67291	P.29	TRIMPOT CEMH 10K K OW50
11 3724	C.83	CAPACITOR POME 100K K5 63	10 67291	P.31	TRIMPOT CEMH 10K K OW50
11 2366	C.84	CAPACITOR N750MI 220P J5 63	10 67291	P.33	TRIMPOT CEMH 10K K OW50
11 2774	C.85	CAPACITOR CE MI 100K U5 63	10 67291	P.34	TRIMPOT CEMH 10K K OW50
11 2774	C.86	CAPACITOR CE MI 100K U5 63	10 67291	P.35	TRIMPOT CEMH 10K K OW50
11 37121	C.87	CAPACITOR POME 10K K5 100	10 67291	P.37	TRIMPOT CEMH 10K K OW50
11 2366	C.94	CAPACITOR N750MI 220P J5 63	10 67291	P.39	TRIMPOT CEMH 10K K OW50
11 2774	C.95	CAPACITOR CE MI 100K U5 63	10 67291	P.41	TRIMPOT CEMH 10K K OW50
11 2774	C.96	CAPACITOR CE MI 100K U5 63	10 67291	P.43	TRIMPOT CEMH 10K K OW50

ITEM NO.	SIT.	DESCRIPTION	ITEM NO.	SIT.	DESCRIPTION
-----	----	-----	-----	----	-----
10 67291	P.44	TRIMPOT CEMH 10K K OW50	10 1144	R.31	RESISTOR CF 4K7 J OW25
10 67291	P.45	TRIMPOT CEMH 10K K OW50	10 1140	R.32	RESISTOR CF 2K2 J OW25
10 67291	P.46	TRIMPOT CEMH 10K K OW50	10 1140	R.33	RESISTOR CF 2K2 J OW25
10 67291	P.47	TRIMPOT CEMH 10K K OW50	10 1143	R.34	RESISTOR CF 3K9 J OW25
10 67291	P.48	TRIMPOT CEMH 10K K OW50	10 1148	R.35	RESISTOR CF 10K J OW25
10 67291	P.49	TRIMPOT CEMH 10K K OW50	10 1144	R.36	RESISTOR CF 4K7 J OW25
10 67291	P.50	TRIMPOT CEMH 10K K OW50	10 1136	R.40	RESISTOR CF 1K J OW25
10 67291	P.51	TRIMPOT CEMH 10K K OW50	10 1136	R.41	RESISTOR CF 1K J OW25
10 67291	P.52	TRIMPOT CEMH 10K K OW50	10 1136	R.42	RESISTOR CF 1K J OW25
10 67291	P.53	TRIMPOT CEMH 10K K OW50	10 1136	R.43	RESISTOR CF 1K J OW25
10 67291	P.54	TRIMPOT CEMH 10K K OW50	10 1136	R.44	RESISTOR CF 1K J OW25
10 67291	P.55	TRIMPOT CEMH 10K K OW50	10 1136	R.45	RESISTOR CF 1K J OW25
10 67291	P.56	TRIMPOT CEMH 10K K OW50	10 1156	R.48	RESISTOR CF 47K J OW25
10 67291	P.57	TRIMPOT CEMH 10K K OW50	10 1156	R.49	RESISTOR CF 47K J OW25
10 67291	P.58	TRIMPOT CEMH 10K K OW50	10 1156	R.50	RESISTOR CF 47K J OW25
10 67291	P.59	TRIMPOT CEMH 10K K OW50	10 1156	R.51	RESISTOR CF 47K J OW25
71 5894	PC..	PC CONV - 7612168	10 1142	R.52	RESISTOR CF 3K3 J OW25
13 14295	Q..1	TRANSISTOR BC549B	10 1146	R.53	RESISTOR CF 6K8 J OW25
13 14131	Q..2	TRANSISTOR BC557B BC307B	10 1142	R.54	RESISTOR CF 3K3 J OW25
13 14295	Q..3	TRANSISTOR BC549B	10 1146	R.55	RESISTOR CF 6K8 J OW25
13 14131	Q..4	TRANSISTOR BC557B BC307B	10 1144	R.57	RESISTOR CF 4K7 J OW25
13 1428	Q..5	TRANSISTOR BC548C BC238C	10 1164	R.58	RESISTOR CF 220K J OW25
13 1428	Q..6	TRANSISTOR BC548C BC238C	10 1164	R.59	RESISTOR CF 220K J OW25
13 1428	Q..7	TRANSISTOR BC548C BC238C	10 1136	R.60	RESISTOR CF 1K J OW25
13 1428	Q..8	TRANSISTOR BC548C BC238C	10 1136	R.61	RESISTOR CF 1K J OW25
13 14295	Q..9	TRANSISTOR BC549B	10 1144	R.62	RESISTOR CF 4K7 J OW25
13 14131	Q.10	TRANSISTOR BC557B BC307B	10 1144	R.63	RESISTOR CF 4K7 J OW25
13 14131	Q.11	TRANSISTOR BC557B BC307B	10 1152	R.64	RESISTOR CF 22K J OW25
13 14295	Q.12	TRANSISTOR BC549B	10 1152	R.65	RESISTOR CF 22K J OW25
13 2528	Q.13	TRANSISTOR BC264B FET	10 1152	R.66	RESISTOR CF 22K J OW25
13 14131	Q.14	TRANSISTOR BC557B BC307B	10 1152	R.67	RESISTOR CF 22K J OW25
13 1428	Q.15	TRANSISTOR BC548C BC238C	10 1140	R.68	RESISTOR CF 2K2 J OW25
13 14295	Q.16	TRANSISTOR BC549B	10 1140	R.69	RESISTOR CF 2K2 J OW25
13 14295	Q.17	TRANSISTOR BC549B	10 1140	R.70	RESISTOR CF 2K2 J OW25
13 14295	Q.18	TRANSISTOR BC549B	10 1140	R.71	RESISTOR CF 2K2 J OW25
13 14131	Q.19	TRANSISTOR BC557B BC307B	10 1148	R.73	RESISTOR CF 10K J OW25
13 14295	Q.20	TRANSISTOR BC549B	10 1148	R.74	RESISTOR CF 10K J OW25
13 14295	Q.21	TRANSISTOR BC549B	10 1148	R.75	RESISTOR CF 10K J OW25
13 14295	Q.22	TRANSISTOR BC549B	10 1136	R.80	RESISTOR CF 1K J OW25
13 14295	Q.23	TRANSISTOR BC549B	10 1136	R.81	RESISTOR CF 1K J OW25
13 14131	Q.24	TRANSISTOR BC557B BC307B	10 1136	R.82	RESISTOR CF 1K J OW25
13 14295	Q.25	TRANSISTOR BC549B	10 1136	R.83	RESISTOR CF 1K J OW25
13 14295	Q.26	TRANSISTOR BC549B	10 1136	R.84	RESISTOR CF 1K J OW25
13 14295	Q.27	TRANSISTOR BC549B	10 1136	R.85	RESISTOR CF 1K J OW25
13 14295	Q.28	TRANSISTOR BC549B	10 1156	R.88	RESISTOR CF 47K J OW25
13 14295	Q.31	TRANSISTOR BC549B	10 1156	R.89	RESISTOR CF 47K J OW25
13 14295	Q.32	TRANSISTOR BC549B	10 1156	R.90	RESISTOR CF 47K J OW25
13 14295	Q.33	TRANSISTOR BC549B	10 1156	R.91	RESISTOR CF 47K J OW25
13 14295	Q.34	TRANSISTOR BC549B	10 1142	R.92	RESISTOR CF 3K3 J OW25
13 30291		TRANSISTOR MICA INSULAT TO-220	10 1146	R.93	RESISTOR CF 6K8 J OW25
13 30292		TRANSISTOR BUSH INSULAT TO-220	10 1142	R.94	RESISTOR CF 3K3 J OW25
10 11209	R..1	RESISTOR CFFUL 47E J OW25	10 1146	R.95	RESISTOR CF 6K8 J OW25
10 1152	R..2	RESISTOR CF 22K J OW25	10 1164	R.98	RESISTOR CF 220K J OW25
10 1136	R..3	RESISTOR CF 1K J OW25	10 1164	R.99	RESISTOR CF 220K J OW25
10 1148	R..4	RESISTOR CF 10K J OW25	10 1136	R100	RESISTOR CF 1K J OW25
10 1149	R..5	RESISTOR CF 12K J OW25	10 1136	R101	RESISTOR CF 1K J OW25
10 1155	R..6	RESISTOR CF 39K J OW25	10 1144	R102	RESISTOR CF 4K7 J OW25
10 1146	R..7	RESISTOR CF 6K8 J OW25	10 1144	R103	RESISTOR CF 4K7 J OW25
10 1142	R..8	RESISTOR CF 3K3 J OW25	10 1152	R104	RESISTOR CF 22K J OW25
10 1140	R..9	RESISTOR CF 2K2 J OW25	10 1152	R105	RESISTOR CF 22K J OW25
10 1140	R.10	RESISTOR CF 2K2 J OW25	10 1152	R106	RESISTOR CF 22K J OW25
10 1159	R.11	RESISTOR CF 82K J OW25	10 1152	R107	RESISTOR CF 22K J OW25
10 1154	R.12	RESISTOR CF 33K J OW25	10 1140	R108	RESISTOR CF 2K2 J OW25
10 1154	R.13	RESISTOR CF 33K J OW25	10 1140	R109	RESISTOR CF 2K2 J OW25
10 1160	R.14	RESISTOR CF 100K J OW25	10 1140	R110	RESISTOR CF 2K2 J OW25
10 1144	R.15	RESISTOR CF 4K7 J OW25	10 1140	R111	RESISTOR CF 2K2 J OW25
10 1148	R.16	RESISTOR CF 10K J OW25	10 1148	R113	RESISTOR CF 10K J OW25
10 1152	R.20	RESISTOR CF 22K J OW25	10 1256	R120	RESISTOR CF 47K J OW50
10 1152	R.21	RESISTOR CF 22K J OW25	10 1136	R121	RESISTOR CF 1K J OW25
10 1144	R.22	RESISTOR CF 4K7 J OW25	10 1155	R122	RESISTOR CF 39K J OW25
10 1140	R.23	RESISTOR CF 2K2 J OW25	10 1136	R123	RESISTOR CF 1K J OW25
10 1140	R.24	RESISTOR CF 2K2 J OW25	10 1148	R124	RESISTOR CF 10K J OW25
10 1148	R.25	RESISTOR CF 10K J OW25	10 1141	R125	RESISTOR CF 2K7 J OW25
10 1148	R.26	RESISTOR CF 10K J OW25	10 1140	R126	RESISTOR CF 2K2 J OW25
10 1148	R.27	RESISTOR CF 10K J OW25	10 1144	R127	RESISTOR CF 4K7 J OW25
10 1148	R.28	RESISTOR CF 10K J OW25	10 1140	R128	RESISTOR CF 2K2 J OW25
10 1152	R.29	RESISTOR CF 22K J OW25	10 1140	R129	RESISTOR CF 2K2 J OW25
10 1152	R.30	RESISTOR CF 22K J OW25	10 1140	R130	RESISTOR CF 2K2 J OW25
			10 1148	R131	RESISTOR CF 10K J OW25
			10 1152	R132	RESISTOR CF 22K J OW25

ITEM NO.	SIT.	DESCRIPTION	ITEM NO.	SIT.	DESCRIPTION
10 1152	R133	RESISTOR CF 22K J W25	10 1148	R225	RESISTOR CF 10K J OW25
10 1176	R134	RESISTOR CF 2M2 J W25	10 1140	R226	RESISTOR CF 2K2 J OW25
10 1160	R135	RESISTOR CF 100K J OW25	10 1140	R227	RESISTOR CF 2K2 J OW25
10 1164	R136	RESISTOR CF 220K J OW25	10 1140	R228	RESISTOR CF 2K2 J OW25
10 1152	R137	RESISTOR CF 22K J OW25	10 1140	R229	RESISTOR CF 2K2 J OW25
10 1156	R138	RESISTOR CF 47K J OW25	10 1152	R240	RESISTOR CF 22K J OW25
10 1156	R139	RESISTOR CF 47K J OW25	10 1136	R241	RESISTOR CF 1K J OW25
10 1144	R141	RESISTOR CF 4K7 J OW25	10 1132	R242	RESISTOR CF 470E J OW25
10 1148	R142	RESISTOR CF 10K J OW25	10 1132	R243	RESISTOR CF 470E J OW25
10 1152	R143	RESISTOR CF 22K J OW25	10 11169	R244	RESISTOR CFFUL 22E J OW25
10 1148	R144	RESISTOR CF 10K J OW25	10 11169	R245	RESISTOR CFFUL 22E J OW25
10 1142	R145	RESISTOR CF 3K3 J OW25	10 11907	R246	RESISTOR CFF E1 J OW40
10 1140	R146	RESISTOR CF 2K2 J OW25	10 11907	R247	RESISTOR CFF E1 J OW40
10 1140	R147	RESISTOR CF 2K2 J OW25	10 1136	R250	RESISTOR CF 1K J OW25
10 1152	R148	RESISTOR CF 22K J OW25	10 1152	R251	RESISTOR CF 22K J OW25
10 1148	R149	RESISTOR CF 10K J OW25	10 1138	R252	RESISTOR CF 1K5 J OW25
10 1142	R150	RESISTOR CF 3K3 J OW25	10 1150	R253	RESISTOR CF 15K J OW25
10 1140	R151	RESISTOR CF 2K2 J OW25	10 1143	R254	RESISTOR CF 3K9 J OW25
10 1140	R152	RESISTOR CF 2K2 J OW25	10 1152	R255	RESISTOR CF 22K J OW25
10 1148	R153	RESISTOR CF 10K J OW25	10 1140	R256	RESISTOR CF 2K2 J OW25
10 1148	R154	RESISTOR CF 10K J OW25	10 1136	R257	RESISTOR CF 1K J OW25
10 1148	R156	RESISTOR CF 10K J OW25	10 1152	R258	RESISTOR CF 22K J OW25
10 1148	R157	RESISTOR CF 10K J OW25	10 1164	R259	RESISTOR CF 220K J OW25
10 1142	R160	RESISTOR CF 3K3 J OW25	10 1152	R260	RESISTOR CF 22K J OW25
10 1152	R161	RESISTOR CF 22K J OW25	10 1152	R261	RESISTOR CF 22K J OW25
10 1152	R162	RESISTOR CF 22K J W25	10 1152	R262	RESISTOR CF 22K J OW25
10 1140	R163	RESISTOR CF 2K2 J W25	10 1152	R263	RESISTOR CF 22K J OW25
10 1140	R164	RESISTOR CF 2K2 J OW25	10 1144	R264	RESISTOR CF 4K7 J OW25
10 1142	R165	RESISTOR CF 3K3 J OW25	10 1137	R265	RESISTOR CF 1K2 J OW25
10 1152	R166	RESISTOR CF 22K J OW25	10 1133	R266	RESISTOR CF 560E J OW25
10 1152	R167	RESISTOR CF 22K J OW25	10 1133	R268	RESISTOR CF 560E J OW25
10 1140	R168	RESISTOR CF 2K2 J OW25	10 1104	R269	RESISTOR CF 2E2 J OW25
10 1140	R169	RESISTOR CF 2K2 J OW25	10 3224	R270	RESISTOR MO 100E J 1W50
10 1148	R171	RESISTOR CF 10K J OW25	10 3620	R271	RESISTOR WW H 4E7 K 4W
10 1148	R173	RESISTOR CF 10K J OW25	10 1136	R300	RESISTOR CF 1K J OW25
10 1148	R174	RESISTOR CF 10K J OW25	10 1152	R301	RESISTOR CF 22K J OW25
10 1148	R175	RESISTOR CF 10K J OW25	10 1138	R302	RESISTOR CF 1K5 J OW25
10 1148	R177	RESISTOR CF 10K J OW25	10 1150	R303	RESISTOR CF 15K J OW25
10 1148	R179	RESISTOR CF 10K J OW25	10 1143	R304	RESISTOR CF 3K9 J OW25
10 1148	R180	RESISTOR CF 10K J OW25	10 1152	R305	RESISTOR CF 22K J OW25
10 1148	R181	RESISTOR CF 10K J OW25	10 1140	R306	RESISTOR CF 2K2 J OW25
10 1148	R184	RESISTOR CF 10K J OW25	10 1136	R307	RESISTOR CF 1K J OW25
10 1148	R185	RESISTOR CF 10K J OW25	10 1152	R308	RESISTOR CF 22K J OW25
10 1148	R188	RESISTOR CF 10K J OW25	10 1164	R309	RESISTOR CF 220K J OW25
10 1148	R189	RESISTOR CF 10K J OW25	10 1152	R310	RESISTOR CF 22K J OW25
10 1148	R190	RESISTOR CF 10K J OW25	10 1152	R311	RESISTOR CF 22K J OW25
10 1148	R191	RESISTOR CF 10K J OW25	10 1152	R312	RESISTOR CF 22K J OW25
10 1152	R192	RESISTOR CF 22K J OW25	10 1152	R313	RESISTOR CF 22K J OW25
10 1148	R193	RESISTOR CF 10K J OW25	10 1144	R314	RESISTOR CF 4K7 J OW25
10 1148	R194	RESISTOR CF 10K J OW25	10 1137	R315	RESISTOR CF 1K2 J OW25
10 1152	R195	RESISTOR CF 22K J W25	10 1133	R316	RESISTOR CF 560E J OW25
10 1140	R196	RESISTOR CF 2K2 J W25	10 1133	R318	RESISTOR CF 560E J OW25
10 1140	R197	RESISTOR CF 2K2 J W25	10 1104	R319	RESISTOR CF 2E2 J OW25
10 1140	R198	RESISTOR CF 2K2 J OW25	10 3224	R320	RESISTOR MO 100E J 1W50
10 1140	R199	RESISTOR CF 2K2 J OW25	10 3620	R321	RESISTOR WW H 4E7 K 4W
10 1148	R200	RESISTOR CF 10K J OW25	10 1136	R350	RESISTOR CF 1K J OW25
10 1148	R201	RESISTOR CF 10K J OW25	10 1152	R351	RESISTOR CF 22K J OW25
10 1152	R202	RESISTOR CF 22K J OW25	10 1138	R352	RESISTOR CF 1K5 J OW25
10 1148	R203	RESISTOR CF 10K J OW25	10 1150	R353	RESISTOR CF 15K J OW25
10 1148	R204	RESISTOR CF 10K J OW25	10 1143	R354	RESISTOR CF 3K9 J OW25
10 1152	R205	RESISTOR CF 22K J OW25	10 1152	R355	RESISTOR CF 22K J OW25
10 1140	R206	RESISTOR CF 2K2 J OW25	10 1140	R356	RESISTOR CF 2K2 J OW25
10 1140	R207	RESISTOR CF 2K2 J OW25	10 1136	R357	RESISTOR CF 1K J OW25
10 1140	R208	RESISTOR CF 2K2 J OW25	10 1152	R358	RESISTOR CF 22K J OW25
10 1140	R209	RESISTOR CF 2K2 J OW25	10 1164	R359	RESISTOR CF 220K J OW25
10 1148	R210	RESISTOR CF 10K J OW25	10 1152	R360	RESISTOR CF 22K J OW25
10 1148	R211	RESISTOR CF 10K J OW25	10 1152	R361	RESISTOR CF 22K J OW25
10 1148	R212	RESISTOR CF 10K J OW25	10 1152	R362	RESISTOR CF 22K J OW25
10 1148	R213	RESISTOR CF 10K J OW25	10 1152	R363	RESISTOR CF 22K J OW25
10 1148	R214	RESISTOR CF 10K J OW25	10 1144	R364	RESISTOR CF 4K7 J OW25
10 1148	R215	RESISTOR CF 10K J OW25	10 1137	R365	RESISTOR CF 1K2 J OW25
10 1148	R216	RESISTOR CF 10K J OW25	10 1133	R366	RESISTOR CF 560E J OW25
10 1148	R217	RESISTOR CF 10K J OW25	10 1133	R368	RESISTOR CF 560E J OW25
10 1148	R218	RESISTOR CF 10K J OW25	10 1104	R369	RESISTOR CF 2E2 J OW25
10 1148	R219	RESISTOR CF 10K J OW25	10 3224	R370	RESISTOR MO 100E J 1W50
10 1148	R220	RESISTOR CF 10K J W25	10 3620	R371	RESISTOR WW H 4E7 K 4W
10 1148	R221	RESISTOR CF 10K J W25	10 1136	R400	RESISTOR CF 1K J OW25
10 1148	R222	RESISTOR CF 10K J W25	10 1152	R401	RESISTOR CF 22K J OW25
10 1148	R223	RESISTOR CF 10K J OW25	10 1138	R402	RESISTOR CF 1K5 J OW25
10 1148	R224	RESISTOR CF 10K J OW25	10 1150	R403	RESISTOR CF 15K J OW25

ITEM NO.	SIT.	DESCRIPTION	ITEM NO.	SIT.	DESCRIPTION
10 1143	R404	RESISTOR CF 3K9 J OW25	76 1289		UN.G2 CONTROL S43 DATA
10 1152	R405	RESISTOR CF 22K J OW25	31 5315	001.	CONNECTOR RIVET MOBTE D 2L14
10 1140	R406	RESISTOR CF 2K2 J OW25	80 0943	0010	SPACER RIV M3
10 1136	R407	RESISTOR CF 1K J OW25	36 20216	0012	SCREW DIN84 M 3 X 6 MP-
10 1152	R408	RESISTOR CF 22K J OW25	36 7502	0013	WASHER LA 3,2 D6798
10 1164	R409	RESISTOR CF 220K J OW25	72 18122	002.	KNOB TURN RED
10 1152	R410	RESISTOR CF 22K J OW25	72 18125	0021	KNOB TURN GREEN
10 1152	R411	RESISTOR CF 22K J OW25	72 18126	0022	KNOB TURN BLUE
10 1152	R412	RESISTOR CF 22K J OW25	80 0927	003.	HEATSINK SMC CONV
10 1152	R413	RESISTOR CF 22K J OW25	36 7455	0031	RIVET AL FE TAP/D/BS46 D3,2
10 1144	R414	RESISTOR CF 4K7 J OW25	13 3029	0032	TRANSISTOR SET INSULAT TO220
10 1137	R415	RESISTOR CF 1K2 J OW25	36 20236	0033	SCREW DIN84 M 3 X10 MP-
10 1133	R416	RESISTOR CF 560E J OW25	36 7502	0034	WASHER LA 3,2 D6798
10 1133	R418	RESISTOR CF 560E J OW25	80 0935	004.	PRO ALU CONV 43
10 1104	R419	RESISTOR CF 2E2 J OW25	36 7455	0041	RIVET AL FE TAP/D/BS46 D3,2
10 3224	R420	RESISTOR MO 100E J 1W50	80 0924	005.	FIXLATH M3 SMC CONV
10 3620	R421	RESISTOR WW H 4E7 K 4W	36 26696	0051	SCREW DIN921 M 3 X 8 MP-
10 1152	R461	RESISTOR CF 22K J OW25	80 0768	006.	SIDE CONV 43
10 1152	R462	RESISTOR CF 22K J OW25	36 33115	0061	SCREW DIN7516 4 X20 MP+C
10 1152	R463	RESISTOR CF 22K J OW25	80 0929	007.	DPL CONV DOWN 43
10 1144	R464	RESISTOR CF 4K7 J OW25	80 1141	008.	DPL CONV UP 43 VERSION2
10 1137	R465	RESISTOR CF 1K2 J OW25	36 20526	009.	SCREW DIN84 M 4 X10 MP-
10 1133	R466	RESISTOR CF 560E J OW25	80 0937	0091	WASHER CONV 43
10 1133	R468	RESISTOR CF 560E J OW25	72 1835	010.	FIX CABLE CONV 43
10 1104	R469	RESISTOR CF 2E2 J OW25	36 20216	0101	SCREW DIN84 M 3 X 6 MP-
10 3224	R470	RESISTOR MO 100E J 1W50	72 1840	011.	CENTERPIECE KNOB CONVERGEN43
10 3620	R471	RESISTOR WW H 4E7 K 4W	36 15075	0111	SCREW DIN7981 3,2X 9,5 PP+
10 3224	R520	RESISTOR MO 100E J 1W50	34 8100	8100	JUMPER 0,6 AUTOMAT
13 1765	Z..1	DIODE ZENER 27V OW5 B			